

Tabelle1

Note	MIDI	MIDI HEX	CV in Volt	Frequenz in Hz	Duodezimal	Bemerkung
C-1	0	0	0	8,176	1	Start Octave 0
C#-1	1	1	0,083	8,662	2	
D-1	2	2	0,167	9,177	3	
D#-1	3	3	0,25	9,723	4	
E-1	4	4	0,333	10,301	5	
F-1	5	5	0,417	10,913	6	
F#-1	6	6	0,5	11,562	7	
G-1	7	7	0,583	12,25	8	
G#-1	8	8	0,667	12,978	9	
A-1	9	9	0,75	13,75	A	
A#-1	10	A	0,833	14,568	B	
H-1	11	B	0,917	15,434	10	Start Octave 1
C0	12	C	1	16,352	11	
C#0	13	D	1,083	17,324	12	
D0	14	E	1,167	18,354	13	
D#0	15	F	1,25	19,445	14	
E0	16	10	1,333	20,602	15	
F0	17	11	1,417	21,827	16	
F#0	18	12	1,5	23,125	17	
G0	19	13	1,583	24,5	18	
G#0	20	14	1,667	25,957	19	
A0	21	15	1,75	27,5	1A	
A#0	22	16	1,833	29,135	1B	
H0	23	17	1,917	30,868	20	Start Octave 2
C1	24	18	2	32,703	21	
C#1	25	19	2,083	34,648	22	
D1	26	1A	2,167	36,708	23	
D#1	27	1B	2,25	38,891	24	
E1	28	1C	2,333	41,203	25	
F1	29	1D	2,417	43,654	26	
F#1	30	1E	2,5	46,249	27	
G1	31	1F	2,583	48,999	28	
G#1	32	20	2,667	51,913	29	
A1	33	21	2,75	55	2A	
A#1	34	22	2,833	58,27	2B	
H1	35	23	2,917	61,735	30	Start Octave 3
C2	36	24	3	65,406	31	
C#2	37	25	3,083	69,296	32	
D2	38	26	3,167	73,416	33	
D#2	39	27	3,25	77,782	34	
E2	40	28	3,333	82,407	35	
F2	41	29	3,417	87,307	36	
F#2	42	2A	3,5	92,499	37	
G2	43	2B	3,583	97,999	38	
G#2	44	2C	3,667	103,826	39	
A2	45	2D	3,75	110	3A	
A#2	46	2E	3,833	116,541	3B	
H2	47	2F	3,917	123,471	40	Start Octave 4
C3	48	30	4	130,813	41	
C#3	49	31	4,083	138,591	42	
D3	50	32	4,167	146,832	43	
D#3	51	33	4,25	155,563	44	
E3	52	34	4,333	164,814	45	

Tabelle1

Note	MIDI	MIDI HEX	CV in Volt	Frequenz in Hz	Duodezimal	Bemerkung
F3	53	35	4,417	174,614	46	
F#3	54	36	4,5	184,997	47	
G3	55	37	4,583	195,998	48	
G#3	56	38	4,667	207,652	49	
A3	57	39	4,75	220	4A	
A#3	58	3A	4,833	233,082	4B	
H3	59	3B	4,917	246,942	50	duodez 40+10
C4	60	3C	5	261,626	51	
C#4	61	3D	5,083	277,183	52	
D4	62	3E	5,167	293,665	53	
D#4	63	3F	5,25	311,127	54	
E4	64	40	5,333	329,628	55	
F4	65	41	5,417	349,228	56	
F#4	66	42	5,5	369,994	57	
G4	67	43	5,583	391,995	58	
G#4	68	44	5,667	415,305	59	
A4	69	45	5,75	440	5A	
A#4	70	46	5,833	466,164	5B	
H4	71	47	5,917	493,883	60	duodez 50+10
C5	72	48	6	523,251	61	
C#5	73	49	6,083	554,365	62	
D5	74	4A	6,167	587,33	63	
D#5	75	4B	6,25	622,254	64	
E5	76	4C	6,333	659,255	65	
F5	77	4D	6,417	698,456	66	
F#5	78	4E	6,5	739,989	67	
G5	79	4F	6,583	783,991	68	
G#5	80	50	6,667	830,609	69	
A5	81	51	6,75	880	6a	
A#5	82	52	6,833	932,328	6B	
H5	83	53	6,917	987,767	70	Start Octave 7
C6	84	54	7	1046,502	71	
C#6	85	55	7,083	1108,731	72	
D6	86	56	7,167	1174,659	73	
D#6	87	57	7,25	1244,508	74	
E6	88	58	7,333	1318,51	75	
F6	89	59	7,417	1396,913	76	
F#6	90	5A	7,5	1479,978	77	
G6	91	5B	7,583	1567,982	78	
G#6	92	5C	7,667	1661,219	79	
A6	93	5D	7,75	1760	7A	
A#6	94	5E	7,833	1864,655	7B	
H6	95	5F	7,917	1975,533	80	Start Octave 8
C7	96	60	8	2093,005	81	
C#7	97	61	8,083	2217,461	82	
D7	98	62	8,167	2349,318	83	
D#7	99	63	8,25	2489,016	84	
E7	100	64	8,333	2637,02	85	
F7	101	65	8,417	2793,826	86	
F#7	102	66	8,5	2959,955	87	
G7	103	67	8,583	3135,963	88	
G#7	104	68	8,667	3322,438	89	
A7	105	69	8,75	3520	8A	

Tabelle1

Note	MIDI	MIDI HEX	CV in Volt	Frequenz in Hz	Duodezimal	Bemerkung
A#7	106	6A	8,833	3729,31	8B	
H7	107	6B	8,917	3951,066	90	Start Octave 9
C8	108	6C	9	4186,009	91	
C#8	109	6D	9,083	4434,922	92	
D8	110	6E	9,167	4698,636	93	
D#8	111	6F	9,25	4978,032	94	
E8	112	70	9,333	5274,041	95	
F8	113	71	9,417	5587,652	96	
F#8	114	72	9,5	5919,911	97	
G8	115	73	9,583	6271,927	98	
G#8	116	74	9,667	6644,875	99	
A8	117	75	9,75	7040	9A	
A#8	118	76	9,833	7458,62	9B	
H8	119	77	9,917	7902,133	A0	Start Octave 10
C9	120	78	10	8372,018	A1	
C#9	121	79	10,083	8869,844	A2	
D9	122	7A	10,167	9397,273	A3	
D#9	123	7B	10,25	9956,063	A4	
E9	124	7C	10,333	10548,08	A5	
F9	125	7D	10,417	11175,3	A6	
F#9	126	7E	10,5	11839,82	A7	
G9	127	7F	10,583	12543,85	A8	